



1 SAT IF distribution equipment Modular optical transmitters

- suitable for SAT IF and CATV application
- option with Web control and SNMP agent functionality marked by letter L, e.g. mo418L
- low signal loss over long distances
- simple installation in the headend with easy module parameter set-up
- loop through RF distribution
- AGC mode for constant laser loading
- manual gain control allows to maintain optimum operation over wide range of input signals
- LED display for easy setup and maintenance
- DIN rail or wall mounting
- robust die-cast housing
- recommended power supplies
- connectors:
 - 3xRF input/output and test - type F
 - optical - SC/APC
 - power distribution bus

mo418
mo428mo418L
mo428L

Technical specifications

| T Y P E | | mo418* | mo428* |
|---------------------------------------|----------------------------------|---|-------------------------|
| Number of optical outputs | | 1 | 2 |
| Optical power | | 1x6 dBm | 2x6 dBm |
| Optical wave lenght | | 1310 ± 10 nm | 1550 ± 3 nm |
| Laser type | | | DFB |
| RF frequency range | | | 47-2400 MHz |
| RF input level | | | 70-85 dB μ V |
| RF input impedance | | | 75 Ω |
| Gain adjustment | | | 0...-15 dB by 1 dB step |
| AGC range | | | ± 5 dB |
| RF input loop through | frequency range | | 47-2400 MHz |
| | loss | | < 1 dB |
| | flatness | | ± 1.0 dB |
| Return loss | | ≥ 18 dB at 40 MHz -1.5 dB/oct (47-950 MHz); ≥ 10 dB up to 1750 MHz; ≥ 7 dB up to 2400 MHz | |
| Relative intensity noise RIN | | < -150 dB/Hz | |
| Terr.TV | intermodulation distortion CSO** | > 60 dB | > 55 dB |
| | intermodulation distortion CTB** | > 62 dB | > 60 dB |
| | carrier/noise ratio C/N** | > 51 dB | > 50 dB |
| SAT IF intermodulation distortions*** | | > 35 dB | |
| Supply voltage | | 12 V ± 1 V | |
| DC feeding for external | | 12 V 0.4 A | |
| Current consumption | | 0.35 A max. | 0.4 A max. |
| Operating temperature range | | 0° ÷ + 50° C | |
| Dimensions/Weight (packed) | | 198x107.5x36 mm/ 0.9 kg | |

* ordering information:

| Type | Laser | Ordering number |
|------------|-----------------|-----------------|
| mo418 4D31 | 6 dBm 1310 nm | 02883 |
| mo418 4D55 | 6 dBm 1550 nm | 02884 |
| mo428 4D31 | 2x6 dBm 1310 nm | 02885 |
| mo428 4D55 | 2x6 dBm 1550 nm | 02886 |

** OMI=4.0 %, 42 channel CENELEC, optical receiver input power -2 dBm

*** OMI=20 %, two tone test metod according EN50083-3

Transmitter features for option with WEB control:

Remotely monitored parameters:

- RF average power
 - laser current
 - external voltage on RF IN
 - supply voltages
 - temperature inside
 - diagnostic information
- Remotely controlled parameters:**
- attenuator level
 - AGC mode
 - switch external voltage on RF

Type Laser Ordering number

| | | |
|-------------|-----------------|--------|
| mo418L 4D31 | 6 dBm 1310 nm | 02883L |
| mo418L 4D55 | 6 dBm 1550 nm | 02884L |
| mo428L 4D31 | 2x6 dBm 1310 nm | 02885L |
| mo428L 4D55 | 2x6 dBm 1550 nm | 02886L |

